

Power Up Procedure (gain venue isolation before commencing power up):

- 1- Turn on three switches in LX control room



- 2- Turn on stage power & basement power on distro panel behind prompt desk.
- 3- Then turn on 13a sockets for DSM desk, Camera on Bar, Monitor and CCTV box on prompt desk & Prompt Side Blue



- 4- Turn on DSM desk (switch top right on desk) and then turn on stage blues (white buttons bottom left of main panel). Turn on fly floor blues (white press button furthest right bottom row of panel beneath green illuminated square)
- 5- Plug DMX into MSL Hazer
- 6- Turn on gods power – upper 32a single phase socket – turn rotary switch to the right.
- 7- Allow Desk op to power on desk
- 8- Turn on DMX controlled Hot Power circuits
- 9- Carry out rig check
- 10- Go into pit and plug IN smoke machine beneath trap.
- 11- Power on projectors – SEE SEPERATE VIDEO POWER ON PROCEDURE
- 12- Check smoke/haze fluid levels

Pre Show Checks:

- 1) Take bike battery and mount to trike (battery charged in LX store). Velcroes in to place on bracket on front of bike – attach battery terminals as per colours.
- 2) Take smoke machine battery off charger, and place next to smoke machine.
- 3) Unplug Micro-USB charging cable from USB battery bank in top of standing lamp, and plug in standard USB-A type connector found in top of standing lamp, in to battery bank (this powers on the wireless DMX receiver box).

Power Down Procedure:

- 1- Unplug DMX from MSL hazer - THIS IS TO ALLOW HAZER TO LOOSE DMX AND GO THROUGH COOL DOWN SEQUENCE
- 2- Use desk to turn off DMX Hot Power
- 3- Power off desk –
- 4- CARRY OUT VIDEO POWER DOWN PROCEDURE – See separate document
- 5- UNPLUG smoke machine in pit
- 6- Turn off three switches in LX control room
- 7- Turn off Gods
- 8- Turn out stage blues, Stage blues (desk and SL doorway 13a plug for Par Can), fly floor
- 9- When clear for ALL OTHER DEPTS - Turn off stage power, basement power and DSM desk, and 13a sockets as per section 3 of power on.

POST SHOW Duties:

- 4) Put bike battery on charge (if matinee) cannot be left to charge overnight
- 5) Put smoke machine battery on trickle charge.
- 6) Put standing lamp USB battery bank on charge – Unplug USB A connector from battery bank, then plug in long Micro USB cable in Ath Kitchen.