

Second Person Narrative

Updated Power Procedure 01/12

Sound Power On -

1. Power on QL5 in Control Room – White plug under desk and switch on back
2. Wait for desk to load and then you can turn on KV2 amps
3. Power on Rio and wait for Dante sync light to turn green
4. Switch on DS Sub and Delay C/L located on Sound Power next to door
5. Switch on Black Plug under control room desk (Delay R)
6. On stage floor switch the USR sound power for US Sub and BP EX6
7. Refer to AV Step 1 and 2
8. Ensure outputs are muted and turn on Mac

AV Power On -

1. Turn on center and SL Projectors with remotes
2. Turn on SR Projector with button located on side
3. Power on laptop

Sound And AV Checks -

1. On AV Laptop open up both files on desktop (QLAB and Glypheo)
2. Ensure Glypheo file is not open full screen but is window is dragged open
3. QLab file should be running in background but not selected (if 2 show day refer to reset list)
4. On Sound Laptop open Dante Controller, DVS and QLab file on desktop
5. Ensure DVS is recognized by controller and minimize software
6. Open Qlab and run tests
7. Fire Sound Test (Cue ST) this will run through all speakers to ensure signal is heard from all
8. Fire AV test (Cue AV0) to ensure OSC is working as expected (if not all screens are displaying ref to troubleshooting guide)
9. Fire AV (AV0.5 and AV0.7) this is to check captioning is working
10. If Bea is not available to check fire cue CQ1 this will load caption “This is a test” on the Centre Screen
11. AV0.9 MUST be fired before the start of the show.
12. Additionally, fire (Cue CQ2) to take Bea to the top of the show.

Reset -

During a 2-show day the AV QLAB will need to be reset to allow for clean operation this can be done in 2 ways -

1. By firing cue AVP (in the av panic group at bottom on QLAB file)
2. Or by manually going to the AV Mac and hitting ESC
3. At this point you can either fire cue C0 or C1 to reset the captions to a black or Test state respectively

AV Troubleshooting -

Refer to Jamie's Documentation for further information -

- The main issue that will occur is that the 2 outputs for SL and Center Screen will swap.
- If AV isn't appearing on expected displays swap the outputs of Optoma 1080p and [Blank] in the settings. (QLab Settings > Video > Output Routing)

Power Down -

- Ensure any changes have been saved
- Repeat Power On process in reverse